

Filed by Express Mail
(Receipt No. 1018087195)
on NOV 10 2002
pursuant to 37 C.F.R. 1.10.
by POPEL

Optical Add-Drop Multiplexing Apparatus

Background of the Invention

Field of the Invention

5 The present invention relates to an optical add-drop multiplexing apparatus, in particular, to that used in a wavelength division multiplexing communication network.

10 Description of the Related Art

 In recent years, as the Internet and cellular phones become common and the functions of terminal units are advanced, the bandwidths of access lines become large and the traffic on the network
15 drastically increases. It seems that such a trend will continue in future. Thus, the infrastructure for communication is being enhanced.

 To deal with the increase of the traffic of communications, an optical communications network
20 is being constructed. To accomplish a large capacity of a transmission line, wavelength division multiplexing (WDM) communications system is being introduced. In comparison with the improvement of the technology with respect to
25 capacity of the transmission line, the improvement

of the technology with respect to speed of communication nodes (transmission devices) is insufficient. Thus, it is pointed out that the communication nodes will become a bottleneck of the network.

Consequently, in a network using the WDM system for accomplishing a large capacity of a transmission line, communication nodes that allow signals to be processed at high speed are required. The mainstream of the network topology is of ring type. The communication nodes are sometimes accomplished by optical add-drop multiplexing apparatuses.

Fig. 1 is a schematic diagram showing the structure of an example of a conventional optical add-drop multiplexing (ADM) apparatus. Referring to Fig. 1, four input-side inter-station lines and four output-side inter-station lines are connected to the optical ADM apparatus. In this example, the inter-station lines are backbone transmission lines that connect communication nodes and transmit multi-wavelength light (λ_1 to λ_n).

Wavelength demultiplexers 501a to 501d demultiplex multi-wavelength light received through the input-side inter-station lines into signals of

individual wavelengths. Cross point switches 502 are disposed corresponding to the individual wavelengths. Input signals are guided to corresponding output ports. Fig. 1 shows a cross point switch 502 corresponding to a wavelength λ_1 . Wavelength multiplexers 503a to 503d multiplex outputs of each cross point switch 502 and output the multiplexed signals to the output-side inter-station lines.

The optical ADM apparatus is provided with an add port and a drop port. The add port is used to receive a signal to be added to an inter-station line. The drop port is used to output a signal branched from an inter-station line to an intra-station line. However, a signal that is input through the add port is branched to a set of signals by an optical coupler that functions as an optical splitter and then guided to the cross point switch 502.

Thus, the cross point switch 502 has eight input ports and six output ports and is realized by an 8 x 6 switch. As shown in Fig. 2, the cross point switch 502 (8 x 6 switch) is composed of thirty five 2 x 2 switches and thirteen 1 x 2 switches.

With the structure, a signal that is input from any input-side inter-station line can be guided to a desired output-side inter-station line or a desired intra-station line. In addition, a
 5 signal that is input from an intra-station line through the add port can be guided to a desired output-side inter-station line.

Fig. 3 is a schematic diagram showing the structure of another example of a conventional
 10 optical ADM apparatus. In this optical ADM apparatus, an optical switch is divided into a plurality of portions. In other words, the optical ADM apparatus comprises 3 x 2 switches 511a to 511d, a 4 x 4 switch 512, 2 x 2 switches 513a and 513b,
 15 and a 4 x 2 switch 514. The 3 x 2 switches 511a to 511d are disposed corresponding to the individual inter-station lines. The 4 x 4 switch 512 are used to switch the route of a signal upon occurrence of a fault. The 2 x 2 switches 513a and 513b are used
 20 to add a signal to a desired inter-station line. The 4 x 2 switch 514 is used to guide a signal branched from an inter-station line to an intra-station line. With this structure, a signal that is input from any line can be guided to a desired line.
 25 However, when large optical switches are used

with the currently available technology, various problems take place. Thus, although the 8 x 6 cross point switch shown in Fig. 2 can be accomplished, it cannot be obtain the high reliability. In addition, the production cost of the switch becomes very high. Thus, considering these points, at least at the present time, the structure of the optical ADM apparatus shown in Fig. 1 is not preferable.

In the optical ADM apparatus shown in Fig. 3, a 4 x 4 switch, 3 x 2 switches, a 4 x 2 switch, and so forth are used instead of a large cross point switch. However, considering the reliability and the production cost, it cannot be said that they are preferable devices for accomplishing an optical ADM apparatus. In other words, it is desired to accomplish an optical ADM apparatus composed of smaller optical switches than those used so far.

When an optical switch used in an optical ADM apparatus gets defective, the defective optical switch is replaced with a new optical switch. Thus, when a large optical switch is used, the unit to be replaced becomes large. In other words, when a large optical switch is maintained, not only a service with respect to a defective line, but a service without respect thereto may have to be

stopped.

Summary of the Invention

An object of the present invention is to
 5 provide an optical ADM apparatus with high
 reliability. Another object of the present
 invention is to provide an optical ADM apparatus
 that can be maintained with a minimum of change or
 stop of services.

10 An optical add/drop multiplexing apparatus of
 the present invention is connected to first to
 fourth input lines, first to fourth output lines,
 an add line, and a drop line, and this apparatus
 comprises: four first optical devices for splitting
 15 signals that are input from the first to fourth
 input lines, respectively; four first switches
 disposed corresponding to the first to fourth
 output lines, respectively; four second switches
 disposed corresponding to the first to fourth
 20 output lines, respectively; a pair of third
 switches; a drop unit for guiding a signal split by
 the first optical devices to the drop line; and an
 add unit for guiding a signal received from the add
 line to the second switches. One of the pair of
 25 third switches guides a signal received from second

switches corresponding to the first and second output lines to first switches corresponding to the third and fourth output lines. The rest of the pair of third switches guides a signal received from second switches corresponding to the third and fourth output lines to first switches corresponding to the first and second output lines. The four first switches output signals split by the first optical devices or signals received from the third switches. The four second switches output signals received from the corresponding first switches or signals received from the add unit to the corresponding output lines.

With this structure, the number of inputs of the first switch is "2", whereas the number of outputs thereof is "1". Thus, the first switch can be accomplished by one switching device. In addition, the number of inputs of each of the second switch and the third switch is "2", whereas the number of outputs thereof is "2". Thus, each of the second switch and the third switch can be accomplished by one switching device. Such switching devices can be produced relatively easily at low cost with high reliability. Thus, an optical Add-Drop multiplexing apparatus with high

reliability can be accomplished.

Brief Description of Drawings

Fig. 1 is a schematic diagram showing the structure of an example of a conventional optical ADM apparatus;

Fig. 2 is a schematic diagram showing the structure of a cross connect switch used in the optical ADM apparatus shown in Fig. 1;

Fig. 3 is a schematic diagram showing the structure of another example of a conventional optical ADM apparatus;

Fig. 4 is a schematic diagram showing the configuration of a network that uses an optical ADM apparatus according to an embodiment of the present invention;

Fig. 5 is a schematic diagram showing a simplified structure of an optical ADM apparatus according to an embodiment of the present invention;

Fig. 6 through Fig. 19 are schematic diagrams showing the structure of an optical ADM apparatus according to first through fourteenth features of the present invention, respectively;

Fig. 20A is a schematic diagram showing an

operation state of a network;

Fig. 20B is a schematic diagram showing the location of a fault that takes place;

Fig. 21 is a schematic diagram for explaining
5 a method for recovering the network from a fault according to the first embodiment;

Fig. 22 is a schematic diagram showing an operation of an optical ADM apparatus in the case that a loop-back operation is performed;

10 Fig. 23A is a schematic diagram showing an operation state of the network;

Fig. 23B is a schematic diagram showing the location of a fault that takes place;

Fig. 24 is schematic diagram for explaining a
15 method for recovering the network from a fault according to the second embodiment;

Fig. 25 is a schematic diagram showing an operation of an optical ADM apparatus in the case that a diverse switching operation is performed;

20 Fig. 26 is a schematic diagram for explaining a method for recovering the network from a fault according to the third embodiment; and

Fig. 27 is a schematic diagram showing an operation of an optical ADM apparatus in the case
25 that a span switching operation is performed.

Description of Preferred Embodiments

With reference to the accompanying drawings,
embodiments of the present invention will be
5 described.

Fig. 4 is a schematic diagram showing the
structure of a network that uses optical add-drop
multiplexing apparatuses (optical ADM apparatuses)
according to an embodiment of the present invention.
10 Referring to Fig. 4, a plurality of optical ADM
apparatuses 1a to 1d are connected in a ring shape.
However, the present invention is not limited to
such a topology.

Each optical ADM apparatus is connected by
15 four optical transmission lines (optical fiber
lines). With these optical transmission lines, a
ring-shaped network is structured. That is, a work
clockwise transmission line, a work
counterclockwise transmission line, a protection
20 clockwise transmission line, and a protection
counterclockwise transmission line are provided. In
this example, "active system" and "backup system"
may be referred to as "W (Work)" and "P
(Protection)", respectively. In addition,
25 "clockwise" and "counterclockwise" may be referred

to as "right-hand rotation" and "left-hand rotation", respectively. Moreover, an optical transmission line that connects optical ADM apparatuses may be referred to as "inter-station line".

On an inter-station line, basically a signal that has been multiplexed in WDM (Wavelength Division Multiplexing) is transmitted. In this example, it is assumed that wavelengths λ_1 to λ_n are used to transmit signals. In addition, basically, signals are transmitted through the work transmission line. When a fault takes place or the work transmission line is maintained, the protection transmission line is used. However, as will be described later, the network can provide a service in such a way that while a regular signal is transmitted through the work transmission line, a low priority signal is transmitted through the protection transmission line.

Each of the optical ADM apparatuses 1a to 1d receives a signal via an input-side inter-station line and outputs the signal to a corresponding output-side inter-station line. In addition, each of the optical ADM apparatuses 1a to 1d can accommodate at least one intra-station line. An

intra-station line is an optical transmission line that connects an optical ADM apparatus and a terminal unit or another node. In the example shown in Fig. 4, a terminal unit 2a is connected to the optical ADM apparatus 1a through an intra-station line and a terminal unit 2b is connected to the optical ADM apparatus 1c through an intra-station line. Each of the optical ADM apparatuses 1a to 1d has a function for adding a signal received through an intra-station line to an inter-station line and another function for guiding a signal received through an inter-station line to an intra-station line. The former function is referred to as "add", whereas the latter function is referred to as "drop".

In addition, the network shown in Fig. 4 provides UPSR (Unidirectional Path Switched Ring). In other words, each of the optical ADM apparatuses 1a to 1d provides a function for performing the UPSR. The UPSR allows one signal to be transmitted through different routes so as to prevent a service from stopping upon occurrence of a fault. That is, when data is transmitted from the terminal unit 2a to the terminal 2b, the optical ADM apparatus 1a transmits the signal from the terminal unit 2b to

the optical ADM apparatus 1c in the clockwise direction. In addition, the optical ADM apparatus 1a transmits the same signal to the optical ADM apparatus 1c in the counterclockwise direction. The
5 optical ADM apparatus 1c selects one of the two signals received from the optical ADM apparatus 1a and transfers the selected signal to the terminal 2b through an intra-station line.

When a fault takes place on the network, a
10 protection inter-station line is used. In this case, an optical ADM apparatus that deals with the fault performs a process for guiding a signal received through the work transmission line to the protection transmission line or a process for
15 guiding a signal received through the protection transmission line to the work transmission line.

In such a manner, each optical ADM apparatus can guide a signal received through any inter-station line to a desired inter-station line or a
20 desired intra-station line and guide a signal received through an intra-station line to a desired inter-station line.

Fig. 5 is a schematic diagram showing a simplified structure of an optical ADM apparatus 1
25 according to an embodiment of the present invention.

The optical ADM apparatus 1 represents one of the optical ADM apparatuses 1a to 1d shown in Fig. 4. Four input-side inter-station lines, four output-side inter-station lines, and intra-station lines
 5 are connected to the optical ADM apparatus 1.

Multi-wavelength light (λ_1 to λ_n) is input from each input-side inter-station line. Each multi-wavelength light is demultiplexed into signals with individual wavelengths by wavelength
 10 demultiplexers 501a to 501d. The demultiplexed signals are guided to corresponding switch circuits 10-1 to 10-n.

The switch circuits 10-1 to 10-n are optical switch circuits disposed corresponding to
 15 individual wavelengths. The switch circuits 10-1 to 10-n guide input signals to output lines designated by a controller (not shown). The structure of each of the switch circuits 10-1 to 10-n is the same. Each of the switch circuits 10-1 to 10-n is
 20 provided with a main switch portion 11, a drop unit 12, and an add unit 13. The controller controls the states of switching devices of the main switch portion 11, the drop unit 12, and the add unit 13.

Under the control of the controller (not
 25 shown), the main switch portion 11 connects an

input-side inter-station line and an output-side inter-station line; an input-side inter-station line and the drop unit 12; or the add unit 13 and an output-side inter-station line. The drop unit 12
 5 accommodates an intra-station line (drop line) and guides a signal split by the main switch portion 11 to an intra-station line. The add unit 13 accommodates an intra-station line (add line) and guides a signal received through an intra-station
 10 line to the main switch portion 11.

Signals that are output from the switch circuits 10-1 to 10-n are multiplexed by wavelength multiplexers 503a to 503d. The wavelength multiplexed signal is transmitted to the next
 15 optical ADM apparatuses through an inter-station line.

Fig. 6 is a schematic diagram showing the structure of an optical ADM apparatus according to a first feature of the present invention. As was
 20 described with reference to Fig. 5, an optical ADM apparatus 1 has a plurality of switch circuits 10-1 to 10-n. However, Fig. 6 shows only one of the switch circuits.

Signals that are output from wavelength
 25 demultiplexers 501a to 501d are split (or branched)

by optical couplers 21a to 21d. The optical couplers 21a to 21d function as optical splitters. One of signals split by each of the optical couplers 21a to 21d is guided to a first input port
 5 of each of 2 x 1 switches 22a to 22d, whereas the other signal is guided to a drop unit 12.

The second input ports of the 2 x 1 switches 22a, 22b, 22c, and 22d are connected to a first output port of a 2 x 2 switch 24b, a second output
 10 port of the 2 x 2 switch 24b, a first output port of a 2 x 2 switch 24a, and a second output port of the 2 x 2 switch 24a, respectively. In addition, signals that are output from the 2 x 1 switches 22a to 22d are guided to first input ports of 2 x 2
 15 switches 23a to 23d, respectively.

Signals that are output from the add unit 13 are guided to second input ports of the 2 x 2 switches 23a to 23d, respectively. Signals that are output from the first output ports of the 2 x 2
 20 switches 23a to 23d are guided to wavelength multiplexers 503a to 503d, respectively. On the other hand, signals that are output from second output ports of the 2 x 2 switches 23a and 23b are guided to the 2 x 2 switch 24a. Signals that are
 25 output from second output ports of the 2 x 2

switches 23c and 23d are guided to the 2 x 2 switch 24b.

As was described above, signals that are output from the 2 x 2 switches 24a and 24b are guided to the 2 x 1 switches 22a to 22d, respectively.

In Fig. 6, the main switch portion 11 is composed of the optical couplers 21a to 21d, the 2 x 1 switches 22a to 22d, the 2 x 2 switches 23a to 23d, and the 2 x 2 switches 24a and 24b.

The drop unit 12 has optical couplers 31a to 31d and 4 x 1 switches 32a and 32b. The drop unit 12 accommodates two intra-station lines (Drop-1 and Drop-2).

The optical couplers 31a to 31d split signals received from the optical couplers 21a to 21d, respectively. The optical couplers 31a to 31d function as optical splitters. One signal split by each of the optical couplers 31a to 31d is guided to the 4 x 1 switch 32a, whereas the other signal split thereby is guided to the 4 x 1 switch 32b. The 4 x 1 switch 32a guides one of the signals received from the optical couplers 31a to 31d to the intra-station line (Drop-1). On the other hand, the 4 x 1 switch 32b guides one of the signals

received from the optical couplers 31a to 31d to the intra-station line (Drop-2).

The add unit 13 has optical couplers 41a and 41b and 2 x 2 switches 42a and 42b. In addition,
 5 the add unit 13 accommodates two intra-station lines (Add-1 and Add-2).

The optical coupler 41a splits a signal received through the intra-station line (Add-1) and guides the split signals to the 2 x 2 switches 42a and 42b. On the other hand, the optical coupler 41b
 10 splits a signal received through the intra-station line (Add-2) and guides the split signals to the 2 x 2 switches 42a and 42b. The optical couplers 41a and 41b function as optical splitter.

15 A first output port of the 2 x 2 switch 42a is connected to a second input port of the 2 x 2 switch 23a. A second output port of the 2 x 2 switch 42a is connected to a second input port of the 2 x 2 switch 23b. Likewise, a first output port
 20 of the 2 x 2 switch 42b is connected to a second input port of the 2 x 2 switch 23c. A second output port of the 2 x 2 switch 42b is connected to a second input port of the 2 x 2 switch 23d.

In this structure, the 2 x 1 switches 22a to
 25 22d are disposed so as to guide signals received

from the input-side inter-station lines to corresponding output-side inter-station lines. The 2 x 2 switches 23a to 23d are disposed so as to select signals received through intra-station lines or signals received through intra-station lines and to guide the selected signals to corresponding output-side inter-station lines. The 2 x 2 switches 24a and 24b are disposed so as to guide a signal to be output to the work line to the protection line and to guide a signal to be output to the protection line to the work line.

Next, the operation of the optical ADM apparatus 1 shown in Fig. 6 will be described.

When a signal received from an adjacent optical ADM apparatus through an inter-station line is transmitted to the next optical ADM apparatus as it is, the 2 x 1 switches 22a to 22d and the 2 x 2 switches 23a to 23d are placed in "bar" state. Thus, a signal received through the input-side inter-station line (W-right) is guided to the output-side inter-station line (W-right) through the optical coupler 21a, the 2 x 1 switch 22a, and the 2 x 2 switch 23a. Likewise, a signal received through another input-side inter-station line is guided to a corresponding output-side inter-station line.

Here, in a 2 x 1 switch, the "bar state" represents the state that a signal of a first input port is guided to an output port, whereas the "cross state" represents the state that a signal of a second input port is guided to an output port. In a 2 x 2 switch, the "bar state" represents the state that a signal of a first input port is guided to a first output port and a signal of a second input port is guided to a second output port, whereas the "cross state" represents the state that a signal of a first input port is guided to a second output port, whereas a signal of a second input port is guided to a first output port.

When a signal received through an input-side inter-station line is dropped to an intra-station line, the 4 x 1 switch 32a or 32b selects a corresponding input port. For example, when a signal received through the input-side inter-station line (W-right) is dropped to the intra-station line (Drop-1), the 4 x 1 switch 32a selects an input port connected to the optical coupler 31a.

In the optical ADM apparatus 1, a signal that is input from an inter-station line is guided to both an output-side inter-station line and the drop unit 12 by the optical couplers 21a to 21d. Thus,

while the optical ADM apparatus 1 relays a signal that is input from an intra-station line to the next optical ADM apparatus, the optical ADM apparatus 1 can drop the same signal to an intra-station line. In the drop unit 12, a signal that is input from an intra-station line is guided to both the 4 x 1 switches 32a and 32b by the optical couplers 31a to 31d. Thus, the same signal can be dropped to the two intra-station lines (Drop-1 and Drop-2).

When a signal received from an intra-station line is added to an inter-station line, the 2 x 2 switch 23a to 23d corresponding to an output-side inter-station line to which the signal is to be added is placed in the "cross state". In addition, the 2 x 2 switch 42a or 42b is controlled so that the signal to be added is guided to a corresponding 2 x 2 switch 23a to 23d. For example, when a signal received from the intra-station line (Add-1) is added to the inter-station line (W-right), the 2 x 2 switch 23a is placed in the "cross state". The 2 x 2 switch 42a is controlled so that the signal is guided to the 2 x 2 switch 23a.

When the UPSR is performed, the 2 x 2 switches 23a to 23d corresponding to two output-side inter-

station lines to which the signal is added are placed in the "cross state". In addition, the 2 x 2 switches 42a and 42b are controlled so that the signal to be added is guided to the corresponding 2 x 2 switch 23a to 23d. For example, when a signal received from the intra-station line (Add-1) is added to both the inter-station line (W-right) and the inter-station line (P-left), the 2 x 2 switches 23a and 23d are placed in the "cross state". In addition, the 2 x 2 switches 42a and 42b are controlled so that the signal is guided to the 2 x 2 switches 23a and 23d.

In a network that performs the UPSR, when a signal received from one route is the same as a signal received from the other route, the drop unit 12 selects one of the received signals. For example, when the same signal is received from the inter-station line (W-right) and the inter-station line (P-left) and the signal received from the inter-station line (W-right) is dropped to an intra-station line, the 4 x 1 switch 32a or 32b selects a signal received from the optical coupler 31a.

When a fault takes place, signals received from the work lines (W-right and W-left) are switched to the protection lines (P-right and P-

left), respectively. Alternatively, signals received from the protection lines are switched to the work lines, respectively. In this case, the 2 x 2 switch 23 (23a to 23d) corresponding to a line to which a signal whose route should be changed is input is placed in the "cross state". In addition, the 2 x 2 switch 24a or 24b connected to that 2 x 2 switch 23 is placed in the "cross state" or the "bar state" depending on whether the signal should be transmitted in the clockwise direction or the counterclockwise direction. In addition, the 2 x 1 switch 22 (22a to 22d) connected to the 2 x 2 switch 24 is placed in the "cross state". Moreover, the 2 x 2 switch 23 (23a to 23d) connected to the 2 x 1 switch 22 is placed in the "bar state".

For example, when a signal that is input from the inter-station line (W-right) is guided to the inter-station line (P-right), the 2 x 2 switch 23a and the 2 x 1 switch 22c are placed in the "cross state". Here, it is assumed that the other switches are basically placed in the "bar state". In this case, a signal that is input from the inter-station line (W-right) is guided to the inter-station line (P-right) through the 2 x 1 switch 22a, the 2 x 2 switch 23a, the 2 x 2 switch 24a, the 2 x 1 switch

22c, and the 2 x 2 switch 23c. Alternatively, when a signal that is input from the inter-station line (W-right) is guided to the inter-station line (P-left), the 2 x 2 switch 23a, the 2 x 2 switch 24a, and the 2 x 1 switch 22d are placed in the "cross state". In this case, a signal that is input from the inter-station line (W-right) is guided to the inter-station line (P-left) through the 2 x 1 switch 22a, the 2 x 2 switch 23a, the 2 x 2 switch 24a, the 2 x 1 switch 22d, and the 2 x 2 switch 23d.

In the structure of the optical ADM apparatus 1 shown in Fig. 6, the number of optical switching devices is much smaller than that in the structure shown in Fig. 1 or 3. In other words, in the optical ADM apparatus shown in Fig. 1, as was described with reference to Fig. 2, 48 optical switching devices are required. On the other hand, in the structure shown in Fig. 3, the 3 x 2 switch, the 4 x 4 switch, and the 4 x 2 switch require 6, 16, and 8 optical switching devices, respectively. Thus, a total of 50 ($= 6 \times 4 + 16 + 8 + 2$) optical switching devices are required.

In contrast, the optical ADM apparatus 1 shown in Fig. 6 has eight 2 x 2 switches, four 2 x 1 switches, and two 4 x 1 switches. Here, one 4 x 1

switch can be composed of three 2×1 switches. In addition, each of the 2×2 switch and the 2×1 switch can be accomplished by one optical switching device, respectively. Thus, the total number of optical switching devices that the optical ADM apparatus 1 has is 18 ($= 8 + 4 + 3 \times 2$).

In addition, switching devices (2×2 switches, 2×1 switches, and so forth) used in the optical ADM apparatus according to the embodiment can be accomplished by reflection type switches that use a technology called MEMS (Micro Mechanical Machine System), Mach-Zehnder type switches, directional coupling type switches, or the like. In particular, since the reflection type switches using the MEMS technology are small and can be easily controlled, they contribute to the size reduction of the switch circuit. As an example of the material of the switching devices, semiconductor, LiNbO_3 or the like is used.

Fig. 7 is a schematic diagram showing the structure of an optical ADM apparatus according to a second feature of the present invention. The structure of the optical ADM apparatus according to the second feature is different from that according to the first feature shown in Fig. 6 in the drop

unit 12.

The drop unit 12 of the optical ADM apparatus according to the second feature has 2 x 2 switches 33a and 33b and 2 x 1 switches 34a and 34b. The 2 x
 5 2 switch 33a guides signals received through the inter-station lines (W-right and W-left) to the 2 x 1 switch 34a and/or the 2 x 1 switch 34b. Likewise, the 2 x 2 switch 33b guides signals received through the inter-station lines (P-right and P-
 10 left) to the 2 x 1 switch 34a and/or 34b. In addition, the 2 x 1 switch 34a guides one of signals received from the 2 x 2 switches 33a and 33b to the intra-station line (Drop-1). Likewise, the 2 x 1 switch 34b guides one of signals received
 15 from the 2 x 2 switches 33a and 33b to the intra-station line (Drop-2).

The optical ADM apparatus shown in Fig. 7 has ten 2 x 2 switches and six 2 x 1 switches. Thus, the number of optical switching devices that the
 20 optical ADM apparatus has amounts to 16 (= 10 + 6).

Since the operation of the optical ADM apparatus according to the second feature is basically the same as that according to the above-described first feature, the description thereof
 25 will be omitted.

Fig. 8 is a schematic diagram showing the structure of an optical ADM apparatus according to a third feature of the present invention. It is assumed that in a system that uses the optical ADM apparatus according to the third feature, a work system and a protection system are disposed for not only inter-station lines, but inter-station lines. In the example, four intra-station lines (Drop-1-W, Drop-1-P, Drop-2-W, and Drop-2-P) are connected to the drop unit 12. Likewise, four intra-station lines (Add-1-W, Add-1-P, Add-2-W, and Add-2-P) are connected to the add unit 13.

The drop unit 12 has four 2 x 2 switches 33a, 33b, 35a, and 35b. The 2 x 2 switch 33a guides signals received through the inter-station lines (W-right and W-left) to the 2 x 2 switch 35a and/or 35b. Likewise, the 2 x 2 switch 33b guides signals received through the inter-station lines (P-right and P-left) to the 2 x 2 switch 35a and/or 35b. In addition, the 2 x 2 switch 35a guides signals received from the 2 x 2 switches 33a and 33b to the intra-station lines (Drop-1-W and Drop-1-P), respectively. Likewise, the 2 x 2 switch 35b guides signals received from the 2 x 2 switches 33a and 33b to the intra-station lines (Drop-2-w and Drop-

2-P), respectively.

With the above-described structure, a signal that is received from a particular inter-station line can be dropped to a desired line of four
5 intra-station lines.

The add unit 13 has four 2 x 2 switches 42a, 42b, 43a, and 43b. The 2 x 2 switch 43a guides signals received through the intra-station lines (Add-1-W and Add-1-P) to the 2 x 2 switch 42a
10 and/or 42b. Likewise, the 2 x 2 switch 43b guides signals received through the intra-station lines (Add-2-W and Add-2-P) to the 2 x 2 switch 42a and/or 42b. In addition, the 2 x 2 switch 42a guides signals received from the 2 x 2 switches 43a
15 and 43b to the 2 x 2 switches 23a and 23b. Likewise, the 2 x 2 switch 42b guides signals received from the 2 x 2 switches 43a and 43b to the 2 x 2 switches 23c and 23d.

With this structure, a signal that is input
20 from a work intra-station line or a protection intra-station line can be added to a desired inter-station line.

Fig. 9 is a schematic diagram showing the structure of an optical ADM apparatus according to
25 a fourth feature of the present invention. The

optical ADM apparatus according to the fourth feature is used in a system of which there are both a regular signal and a low priority signal. In this example, a regular signal is basically transmitted through the work line. On the other hand, a low priority signal is transmitted through the protection line when the protection line is not used for the regular signal. Thus, when the regular signal is transmitted through the protection line due to any reason, the transmission of the low priority signal is stopped. In the specification, the low priority signal may be referred to as "extra traffic".

The basic structure of the optical ADM apparatus according to the fourth feature is the same as that according to the first feature shown in Fig. 6 except that the drop unit 12 has a function for dropping a low priority signal and that the add unit 13 has a function for adding a low priority signal. The drop unit 12 accommodates four intra-station lines (Drop-1, Drop-2, ET-1, and ET-2). The add unit 13 accommodates four intra-station lines (Add-1, Add-2, ET-1, and ET-2).

In addition to the optical couplers 31a to 31d and the 4 x 1 switches 32a and 32b shown in Fig. 6,

the drop unit 12 has 1 x 2 switches 36a and 36b and a 2 x 2 switch 37. The 1 x 2 switch 36a is disposed between an optical coupler 21c and an optical coupler 31c. A signal received from the optical coupler 21c is guided to the optical coupler 31c or the 2 x 2 switch 37. On the other hand, the 1 x 2 switch 36b is disposed between an optical coupler 21d and an optical coupler 31d. A signal received from the optical coupler 21d is guided to the optical coupler 31d or the 2 x 2 switch 37. The 2 x 2 switch 37 guides signals that are output from the 1 x 2 switches 36a and 36b to the intra-station lines (ET-1 and ET-2).

In addition to the optical couplers 41a and 41b and the 2 x 2 switches 42a and 42b shown in Fig. 6, the add unit 13 has a 2 x 2 switch 44 and 2 x 1 switches 45a and 45b. The 2 x 2 switch 44 guides signals received from the intra-station lines (ET-1 and ET-2) to the 2 x 1 switches 45a and 45b. The 2 x 1 switch 45a is disposed between the 2 x 2 switch 42a and the 2 x 2 switch 23c. The 2 x 1 switch 45a selects a signal received from the 2 x 2 switch 42b or a signal received from the 2 x 2 switch 44 and guides the selected signal to the 2 x 2 switch 23c. On the other hand, the 2 x 1 switch 45b is disposed

between the 2 x 2 switch 42b and the 2 x 2 switch 23d. The 2 x 1 switch 45b selects a signal received from the 2 x 2 switch 42b or a signal received from the 2 x 2 switch 44 and guides the selected signal
 5 to the 2 x 2 switch 23d.

In this structure of the optical ADM apparatus, when a low priority signal is added to an inter-station line, the 2 x 2 switch 44 is controlled depending on whether the low priority signal is to
 10 be transmitted in the clockwise direction or the counterclockwise direction. In addition, the 2 x 1 switches 45a and 45b are controlled so that a signal received from the 2 x 2 switch 44 is selected. Moreover, the 2 x 2 switch 23c or 23d is
 15 controlled so that a signal received from the 2 x 1 switch 45a or 45b is guided to an output-side inter-station line, respectively.

For example, when a low priority signal received from the intra-station line (ET-1) is
 20 added to the inter-station line (P-right), the 2 x 2 switch 44 is placed in the "cross state". The 2 x 1 switch 45a is controlled so that a signal received from the 2 x 2 switch 44 is selected. The 2 x 2 switch 23c is placed in the "cross state".
 25 Thus, the low priority signal received from the

intra-station line (ET-1) is guided to the inter-station line (P-right) through the 2 x 2 switch 44, the 2 x 1 switch 45a, and the 2 x 2 switch 23c.

When the protection inter-station lines (P-right and P-left) are used to transmit regular signals, the 2 x 1 switches 45a and 45b are controlled so that a signal received from the 2 x 2 switch 42b is selected. Thus, the low priority signal is not added to the inter-station line.

When a low priority signal received from an inter-station line is dropped, the 1 x 2 switches 36a and 36b are controlled so that signals received from the optical couplers 21c and 21d are guided to the 2 x 2 switch 37. The 2 x 2 switch 37 is controlled so that the received signals are guided to the predetermined intra-station lines (ET-1 or ET-2).

For example, when a low priority signal is dropped from the inter-station line (P-right) to the intra-station line (ET-1), the 1 x 2 switch 36a is controlled so that a signal received from the optical coupler 21c is guided to the 2 x 2 switch 37. Then, the 2 x 2 switch 37 is placed in the "cross state". Thus, the low priority signal received from the inter-station line (P-right) is

guided to the intra-station line (ET-1) through the 1 x 2 switch 36a and the 2 x 2 switch 37.

When the protection inter-station lines (P-right and P-left) are used to transmit regular signals, the 1 x 2 switches 36a and 36b are controlled so that signals received from the optical couplers 21c and 21d are guided to the optical couplers 31c and 31d, respectively. Thus, regular signals received through the protection inter-station lines are dropped to the intra-station lines (Drop-1 and Drop-2).

Fig. 10 is a schematic diagram showing the structure of an optical ADM apparatus according to a fifth feature of the present invention. The optical ADM apparatus according to the fifth feature is accomplished by replacing the 1 x 2 switches 36a and 36b according to the fourth feature shown in Fig. 9 with optical couplers 38a and 38b, respectively. In this feature, the optical coupler 38a guides a signal received from an optical coupler 21c to both the optical coupler 31c and the 2 x 2 switch 37. On the other hand, the optical coupler 38b guides a signal received from an optical coupler 21d to both the optical coupler 31d and the 2 x 2 switch 37. The optical couplers

38a and 38b function as optical splitters.

The operation of the optical ADM apparatus according to the fifth feature is basically the same as the operation of the optical ADM apparatus according to the fourth feature. However, in the structure according to the fifth feature, when low priority signals are transmitted through the protection inter-station lines (P-right and P-left), the low priority signals are guided to not only the 2 x 2 switch 37, but 4 x 1 switches 32a and 32b. Thus, the 4 x 1 switches 32a and 32b should be properly controlled so that signals received from the work inter-station lines (W-right and W-left) are selected.

Fig. 11 is a schematic diagram showing the structure of an optical ADM apparatus according to a sixth feature of the present invention. The basic structure of the optical ADM apparatus according to the sixth feature is the same as that according to the second feature shown in Fig. 7 except that the drop unit 12 has a function for dropping a low priority signal and that the add unit 13 has a function for adding a low priority signal.

As with the fourth feature, the function for dropping a low priority signal is accomplished by

the 1 x 2 switches 36a and 36b and the 2 x 2 switch 37. However, the 1 x 2 switch 36a guides a signal received from the optical coupler 21c to the 2 x 2 switch 33b or the 2 x 2 switch 37. Likewise, the 1 x 2 switch 36b guides a signal received from the optical coupler 21d to the 2 x 2 switch 33b or the 2 x 2 switch 37. On the other hand, as with the fourth feature, the function for adding a low priority signal is accomplished by the 2 x 2 switch 44 and the 2 x 1 switches 45a and 45b. Thus, the method for adding/dropping a low priority signal according to the sixth feature is the same as that according to the fourth feature.

Fig. 12 is a schematic diagram showing the structure of an optical ADM apparatus according to a seventh feature of the present invention. The optical ADM apparatus according to the seventh feature can be accomplished by replacing the 1 x 2 switches 36a and 36b according to the sixth feature shown in Fig. 11 with the optical couplers 38a and 38b. In this feature, the optical coupler 38a guides a signal received from the optical coupler 21c to both the 2 x 2 switch 33b and the 2 x 2 switch 37. Likewise, the optical coupler 38b guides a signal received from the optical coupler 21d to

both the 2 x 2 switch 33b and the 2 x 2 switch 37. Thus, the method for adding/dropping a low priority signal according to the seventh feature is the same as that according to the fifth feature.

5 Fig. 13 is a schematic diagram showing the structure of an optical ADM apparatus according to an eighth feature of the present invention. The basic structure of the optical ADM apparatus according to the eighth feature is the same as that
10 according to the third feature shown in Fig. 8 except that the drop unit 12 has a function for dropping a low priority signal and that the add unit 13 has a function for adding a low priority signal.

15 As with the fourth feature or the sixth feature, the function for dropping a low priority signal is accomplished by the 1 x 2 switches 36a and 36b and the 2 x 2 switch 37. Likewise, as with the fourth feature or the sixth feature, the
20 function for adding a low priority signal is accomplished by the 2 x 2 switch 44 and the 2 x 1 switches 45a and 45b. Thus, the method for adding/dropping a low priority signal according to the eighth feature is the same as that according to
25 the fourth feature or the sixth feature.

Fig. 14 is a schematic diagram showing the structure of an optical ADM apparatus according to a ninth feature of the present invention. The optical ADM apparatus according to the ninth
5 feature is accomplished by replacing the 1 x 2 switches 36a and 36b according to the eighth feature shown in Fig. 13 with the optical couplers 38a and 38b, respectively. In this feature, the optical coupler 38a guides a signal received from
10 the optical coupler 21c to both the 2 x 2 switch 33b and the 2 x 2 switch 37. Likewise, the optical coupler 38b guides a signal received from the optical coupler 21d to both the 2 x 2 switch 33b and the 2 x 2 switch 37. Thus, the method for
15 adding/dropping a low priority signal according to the ninth feature is the same as that according to the fifth feature or the seventh feature.

Fig. 15 is a schematic diagram showing the structure of an optical ADM apparatus according to
20 a tenth feature of the present invention. The structure of the drop unit 12 and the add unit 13 according to the tenth feature is the same as the structure shown in Fig. 6. Alternatively, the structure of the drop unit 12 and the add unit 13
25 may be the same as one of the structures shown in

Figs. 7 to 14.

Referring to Fig. 15, four input-side inter-station lines are connected to a-ports of optical circulators 51a to 51d. On the other hand, four
 5 output-side inter-station lines are connected to c-ports of the optical circulators 51a to 51d. b-ports of the optical circulators 51a to 51d are connected to wavelength multiplexing/demultiplexing devices 52a to 52d, respectively. Each of the
 10 optical circulators 51a to 51d guides a signal that is input from the a-port to the b-port and guides a signal that is input from the b-port to the c-port. Thus, multi-wavelength light (λ_1 to λ_n) that is input from the input-side inter-station lines is
 15 guided to the wavelength multiplexing/demultiplexing devices 52a to 52d.

The wavelength multiplexing/demultiplexing devices 52a to 52d demultiplex the multi-wavelength light received from the optical circulators 51a to
 20 51d to signals with individual wavelengths and guide the demultiplexed signals to corresponding switch circuits. As was described with reference to Fig. 5, switch circuits are disposed corresponding to the wavelengths.

25 Signals demultiplexed by the wavelength

multiplexing/demultiplexing devices 52a to 52d are
 guided to a-ports of optical circulators 53a to 53d.
 b-ports of the optical circulators 53a to 53d are
 connected to the optical couplers 21a to 21d,
 5 respectively. c-ports of the optical circulators
 53a to 53d are connected to first output ports of 2
 x 2 switches 23a to 23d, respectively. Each of the
 optical circulators 53a to 53d guides a signal that
 is input from the a-port to the b-port and guides a
 10 signal that is input from the c-port to the a-port.
 Thus, signals demultiplexed by the wavelength
 multiplexing/demultiplexing devices 52a to 52d are
 guided to the optical couplers 21a to 21d,
 respectively. In addition, signals that are output
 15 from first output ports of the 2 x 2 switches 23a
 to 23d are guided to the wavelength
 multiplexing/demultiplexing devices 52a to 52d,
 respectively.

Since the structures of the optical couplers
 20 21a to 21d, the 2 x 1 switches 22a to 22d, the 2 x
 2 switches 23a to 23d, the 2 x 2 switches 24a and
 24b, the drop unit 12, and the add unit 13
 according to the tenth feature are the same as
 those shown in Figs. 6 to 14, their description
 25 will be omitted.

In this structure, multi-wavelength light that is input from the input-side inter-station lines is guided to the wavelength multiplexing/demultiplexing devices 52a to 52d by the optical circulators 51a to 51d, respectively. The multi-wavelength light is demultiplexed to signals with individual wavelengths. The demultiplexed signals are guided to the optical couplers 21a to 21d by the optical circulators 53a to 53d, respectively.

The operations of the optical couplers 21a to 21d, the 2 x 1 switches 22a to 22d, the 2 x 2 switches 23a to 23d, the 2 x 2 switches 24a and 24b, the drop unit 12, and the add unit 13 of the optical ADM apparatus according to the tenth feature are the same as those of the optical ADM apparatuses described above. Thus, signals to be guided to output-side inter-station lines are output from the 2 x 2 switches 23a to 23d, respectively. The signals that are output from the 2 x 2 switches 23a to 23d are guided to the wavelength multiplexing/demultiplexing devices 52a to 52d by the optical circulators 53a to 53d, respectively. These signals are multiplexed with signals that are output from the other switch

circuits. Multi-wavelength light that is output from the wavelength multiplexing/demultiplexing devices 52a to 52d is guided to output-side inter-station lines by the optical circulators 51a to 51d, respectively. When signals received from the intra-station lines (Add-1 and Add-2) are added to particular inter-station lines, the signals are guided to the inter-station lines through the 2 x 2 switch 23, the optical circulator 53, the wavelength multiplexing/demultiplexing device 52, and the optical circulator 51 corresponding thereto.

Fig. 16 is a schematic diagram showing the structure of an optical ADM apparatus according to an eleventh feature of the present invention. According to the eleventh feature, the structures of the main switch portion 11, the drop unit 12, and the add unit 13 may be the same as those shown in Figs. 6 to 15.

The optical ADM apparatus according to the eleventh feature has a function for compensating the light levels of signals corresponding to the number of switching devices through which these signals pass. This function is accomplished by variable attenuators (VATs) 61a to 61d and a VAT monitoring and controlling unit 62. The variable

attenuators (VATs) 61a to 61d are disposed between first output ports of the 2 x 2 switches 23a to 23d and wavelength multiplexers 503a to 503d, respectively. The VAT monitoring and controlling unit 62 controls the attenuation amounts of each of the variable attenuators (VATs) 61a to 61d.

The VAT monitoring and controlling unit 62 generates control signals for controlling the variable attenuators 61a to 61d according to the states of the individual switches of the optical ADM apparatus. That is, the VAT monitoring and controlling unit 62 detects the number of switches through which signals guided to the individual output-side inter-station lines have passed in the optical ADM apparatus corresponding to switch selection information and generates control signals corresponding to the number of switches that has been detected. The switch selection information is information that designates the states of each switch (for example, bar state/cross state). The switch selection information is generated by a controller (not shown).

When a signal that is input from the inter-station line (W-right) is guided to the inter-station line (W-right) as it is, since the signal

is guided to an output-side inter-station line through the 2 x 1 switch 22a and the 2 x 2 switch 23a, the number of switches through which the signal has passed is "2". On the other hand, when a
5 signal that is input from the inter-station line (W-right) is output to the inter-station line (P-left), since the signal is guided to an output-side inter-station line through the 2 x 1 switch 22a, the 2 x 2 switch 23a, the 2 x 2 switch 24a, the 2 x
10 1 switch 22d, and the 2 x 2 switch 23d, the number of switches through which the signal has passed is "5". Assuming that the optical loss at each switch is 0.3 dB, the difference between the losses of the two routes is around 0.9 dB.

15 The VAT monitoring and controlling unit 62 controls the attenuation amounts for the variable attenuators 61a to 61d so that the difference between the losses is compensated. Thus, with this structure of the optical ADM apparatus, the optical
20 levels of signals guided to individual inter-station lines become the same.

Fig. 17 is a schematic diagram showing the structure of an optical ADM apparatus according to a twelfth feature of the present invention. As with
25 the eleventh feature, the optical ADM apparatus

according to the twelfth feature has a function for causing optical levels of signals to be guided to the individual inter-station lines to be equalized. However, the structure that accomplishes the function according to the twelfth feature is different from that according to the eleventh feature.

In the optical ADM apparatus according to the twelfth feature, variable attenuators 61a to 61d and optical couplers 63a to 63d are disposed between first output ports of 2 x 2 switches 23a to 23d and multiplexers 503a to 503d, respectively. The optical couplers 63a to 63d function as optical splitters. The optical couplers 63a to 63d split signals that are output from the variable attenuators 61a to 61d and guides the signals to the multiplexers 503a to 503d and a VAT monitoring and controlling unit 64. At that point, the splitting ratio of each of the optical couplers 63a to 63d is $n : 1$ (where n is sufficiently larger than 1). The optical level of a signal guided to the VAT monitoring and controlling unit 64 is sufficiently smaller than that of a signal that is output to an inter-station line.

The VAT monitoring and controlling unit 64

monitors the optical levels of individual signals received from the optical couplers 63a to 63d and controls the attenuation amounts for the variable attenuators 61a to 61d so that the light levels of the signals become the same. In other words, the optical levels of the signals to be transmitted to inter-station lines are controlled in a feedback system. Thus, the optical levels of signals to be transmitted to the inter-station lines become the same.

Fig. 18 is a schematic diagram showing the structure of an optical ADM apparatus according to a thirteenth feature of the present invention. The optical ADM apparatus according to the thirteenth feature has a function for equalizing multi-wavelength light for each inter-station line. This function is accomplished by the variable attenuators 61a to 61d, optical couplers 65a to 65d, and a VAT monitoring and controlling unit 66. The variable attenuators 61a to 61d are disposed between first output ports of 2 x 2 switches 23a to 23d and multiplexers 503a to 503d, respectively. The optical couplers 65a to 65d are disposed at outputs of the multiplexers 503a to 503d, respectively. The VAT monitoring and controlling

unit 66 controls the attenuation amounts of the variable attenuators 61a to 61d. Fig. 18 shows only a switch circuit for a particular wavelength. However, the VAT monitoring and controlling unit 66
 5 controls the variable attenuators 61a to 61d of all switch circuits 10-1 to 10-n.

The optical couplers 65a to 65d function as optical splitters. Multi-wavelength light that is output from the multiplexers 503a to 503d is guided
 10 to corresponding inter-station lines. A part of the multi-wavelength light is guided to the VAT monitoring and controlling unit 66. The splitting ratio of each of the optical couplers 65a to 65d is $n : 1$ (where n is a value sufficiently larger than
 15 1). The optical level of the multi-wavelength light guided to the VAT monitoring and controlling unit 64 is sufficiently smaller than that of multi-wavelength light that is output to inter-station lines.

20 The VAT monitoring and controlling unit 66 monitors wavelength characteristics of multi-wavelength light received from the optical couplers 65a to 65d. That is, the VAT monitoring and controlling unit 66 monitors the optical levels of
 25 the individual channels contained in the multi-

wavelength light. The VAT monitoring and controlling unit 66 controls the attenuation amounts of the variable attenuators 61a to 61d of the switch circuits 10-1 to 10-n so that the multi-wavelength light is equalized for the individual inter-station lines. Thus, the multi-wavelength light that is guided to the individual inter-station lines is equalized.

Fig. 19 is a schematic diagram showing the structure of an optical ADM apparatus according to a fourteenth feature of the present invention. The optical ADM apparatus according to the fourteenth feature is accomplished by combining the functions described in the eleventh to thirteenth features shown in Figs. 16 to 18. The optical ADM apparatus shown in Fig. 19 has the three functions according to the eleventh to thirteenth features. Alternatively, the optical ADM apparatus according to the fourteenth feature may have any two of the three functions.

In the structures shown in Figs. 16 to 19, the variable attenuators 61a to 61d for adjusting the optical levels of signals are disposed. Alternatively, optical amplifiers may be used instead of variable attenuators.

Next, a fault recovering function of the optical ADM apparatus according to the present invention will be described. In the following description, it is assumed that a fault takes place
5 on a communication network of which a plurality of optical ADM apparatuses are connected in a ring shape.

First Embodiment

According to a first embodiment, as shown in
10 Fig. 20A, a network is configured in such a manner that six optical ADM apparatuses (ADM #1 to ADM #6) are connected in a ring shape. As was described with reference to Fig. 4, each optical ADM apparatus is connected with four inter-station
15 lines (W-right, W-left, P-right, and P-left). In addition, currently, using a particular wavelength λ_1 , channels A to C have been assigned. The channel A is a communication channel for bi-directionally transmitting a signal between the ADM #1 and the
20 ADM #4 using two work lines (W-right and W-left). Likewise, the channel B is a communication channel for bi-directionally transmitting a signal between the ADM #1 and the ADM #5 using the two work lines. The channel C is a communication channel for bi-
25 directionally transmitting a signal between the ADM

#4 and the ADM #5 using the two work lines.

In such a situation, as shown in Fig. 20B, it is assumed that a fault takes place on a transmission line between the ADM #2 and the ADM #3.

5 In this example, it is assumed that faults take place on all four optical fiber lines disposed between the ADM #2 and the ADM #3. In this case, an operation for recovering the channel A from a fault is performed.

10 Fig. 21 is a schematic diagram showing the state that the channel A is recovered from a fault by loop-back operation according to the BLSR (Bi-directional Line Switching Ring).

The loop-back operation shown in Fig. 21 is performed by an optical ADM apparatus that is connected to a transmission line on which a fault takes place in such a manner that a signal received from a work line is output to a protection line and a signal received from a protection line is output to a work line. According to the embodiment, such a switching operation is performed in the ADM #2 and the ADM #3. As a result, a signal that flows from the ADM #1 to the ADM #4 is transferred to the ADM #2 using the work line. Then, the signal is transmitted to the ADM #3 through the ADM #1, the

15

20

25

ADM #6, the ADM #5, and the ADM #4 using the protection line. Thereafter, the signal is transmitted to the ADM #4 using the work line. On the other hand, a signal that flows from the ADM #4 to the ADM #1 is transmitted in the reverse direction on the route.

Fig. 22 is a schematic diagram showing an operation of an optical ADM apparatus that performs the loop-back operation shown in Fig. 21. Fig. 22 shows a switching operation of the ADM #2 shown in Fig. 21.

When the network is in the state shown in Fig. 20A, the ADM #2 outputs a signal received through the inter-station line (W-right) to the inter-station line (W-right) and outputs a signal received through the inter-station line (W-left) to the inter-station line (W-left). As shown in Fig. 20B, when a fault takes place between the ADM #2 and the ADM #3, the ADM #2 cannot receive a signal transmitted from the ADM #3. In other words, the ADM #2 cannot receive a signal from the inter-station line (W-left). When the ADM #2 has determined that it cannot receive the signal from the inter-station line (W-left), the ADM #2 controls each switch as follows.

The 2 x 1 switch 22a is placed in the "bar state". The 2 x 2 switch 23a is placed in the "cross state". The 2 x 2 switch 24a is placed in the "cross state". The 2 x 1 switch 22d is placed in the "cross state". The 2 x 2 switch 23d is placed in the "bar state". Thus, when a signal that is transmitted from the ADM #1 is input to the ADM #2 through the inter-station line (W-right), as denoted by a solid line in Fig. 22, the signal is guided to the inter-station line (P-left) through the 2 x 1 switch 22a, the 2 x 2 switch 23a, the 2 x 2 switch 24a, the 2 x 1 switch 22d, and the 2 x 2 switch 23d.

The above-described switching operation is also performed by the ADM #3. However, the ADM #3 performs a switching operation in such a manner that a signal transmitted from the ADM #4 through the inter-station line (W-left) is looped back to the inter-station line (P-right). Thus, the ADM #2 receives the signal that is transmitted from the ADM #4 through the inter-station line (P-right). The ADM #2 controls each switch as follows.

The 2 x 1 switch 22c is placed in the "bar state". The 2 x 2 switch 23c is placed in the "cross state". The 2 x 2 switch 24b is placed in

the "cross state". The 2 x 1 switch 22b is placed in the "cross state". The 2 x 2 switch 23b is placed in the "bar state". Thus, when a signal that is transmitted from the ADM #4 is input to the ADM #2 through the inter-station line (P right), as denoted by a broken line in Fig. 22, the signal transmitted is guided to the inter-station line (W-left) through the 2 x 1 switch 22c, the 2 x 2 switch 23c, the 2 x 2 switch 24b, the 2 x 1 switch 22b, and the 2 x 2 switch 23b.

The switching operation is also performed by the ADM #3. However, the ADM #3 performs a switching operation in such a manner that a signal that is transmitted through the inter-station line (P-left) is looped back to the inter-station line (W-right).

In such a manner, the optical ADM apparatus according to the embodiment can recover from a fault with the loop-back function of the BLSR.

20 Second Embodiment

As shown in Fig. 23A, the network configuration and the operation state before occurrence of a fault according to the second embodiment are the same as those according to the first embodiment.

In such a state, it is assumed that as shown in Fig. 23B a fault takes place on a transmission line between the ADM #5 and the ADM #6. In this example, it is assumed that faults take place on
5 all four optical fiber lines disposed between the ADM #5 and the ADM #6. In this case, an operation for recovering the channel B is performed.

Fig. 24 is a schematic diagram showing the state that the channel B is recovered using a
10 diverse switching operation of the BPSR (Bi-directional Path Switched Ring).

When one optical ADM apparatus adds a signal to a channel that is disconnected due to a fault and another optical ADM apparatus drops a signal
15 from the channel, these optical ADM apparatuses perform a diverse switching operation so as to recover from a defect. That is, the optical ADM apparatus that adds a signal to the channel changes the switching state from a state where a signal is
20 added to a work line in one direction to a state where the signal is added to a protection line in the other direction. On the other hand, the optical ADM apparatus that drops the signal from the channel changes the switching state from a state
25 where the signal is dropped from the work line in

one direction to a state where the signal is dropped from the protection line in the other direction.

According to the embodiment, the ADM #1 and
5 the ADM #5 perform the above-described switching operations. As a result, a signal that flows from the ADM #1 to the ADM #5 is transmitted to the ADM #5 through the ADM #2, the ADM #3, and the ADM #4 using a protection line. On the other hand, a
10 signal that flows from the ADM #5 to the ADM #1 is transmitted on the same route in the reverse direction.

Basically, a fault on a transmission line is detected by an optical ADM apparatus connected
15 thereto. Thus, when an optical ADM apparatus that adds/drops a signal is not connected to the transmission line on which the fault takes place, the optical ADM apparatus that has detected the fault sends to an optical ADM apparatus that
20 adds/drops the signal a message that represents that the fault takes place. The optical ADM apparatus that adds/drops the signal performs the diverse switching operation corresponding to the message. The message may be sent using an inter-
25 station line on which a fault does not take place.

Alternatively, the message may be sent using another medium.

Fig. 25 is a schematic diagram showing an operation of an optical ADM apparatus that performs the diverse switching operation shown in Fig. 24. Fig. 25 shows the switching operation of the ADM #5.

Before a fault takes place, as denoted by a dotted line in Fig. 25, the ADM #5 guides a signal received from the intra-station line (Add-1) to the inter-station line (W-right). At that time, as shown in Fig. 24B, a fault takes place on a transmission line between the ADM #5 and the ADM #6. When the ADM #5 receives a message that represents that the fault takes place, the ADM #5 controls each switch as follows. In other words, the 2 x 2 switch 42b is placed in the "cross state". The 2 x 2 switch 23d is placed in the "cross state". Thus, a signal received from the intra-station line (Add-1) is guided to the inter-station line (P-left) through the 2 x 2 switch 42b and the 2 x 2 switch 23d as denoted by a solid line in Fig. 25.

The above-described switching operation is also performed by the ADM #1. However, in the ADM #1, a switching state is designated so that a signal received from a particular intra-station

line is guided to the inter-station line (P-right). Thus, the ADM #5 receives a signal that has been added by the ADM #1 through the inter-station line (P-right). The ADM #5 is controlled so that the 4 x 1 switch 32a selects a signal guided through the optical coupler 31c. Thus, when the signal transmitted from the ADM #1 is input to the ADM #5 through the inter-station line (P-right), as denoted by a solid line in Fig. 25, the signal transmitted from the ADM #1 is guided to the intra-station line (Drop-1) through the optical coupler 21c, the optical coupler 31c, and the 4 x 1 switch 32a.

The switching operation is also performed by the ADM #1. However, the ADM #1 performs the switching operation in such a manner that a signal transmitted through the inter-station line (P-left) is guided to a corresponding intra-station line.

In such a manner, the optical ADM apparatus according to the embodiment can recover from a fault by the diverse switching operation of the BPSR.

Third Embodiment

The configuration of the network and the operation state before an occurrence of a fault

according to the third embodiment are the same as those according to the first embodiment shown in Fig. 20A. As with the first embodiment, it is assumed that a fault takes place on a transmission line between the ADM #2 and the ADM #3. However, unlike with the first embodiment, in the third embodiment, faults take place only on the work lines (W-right and W-left) of the four optical fiber lines disposed between the ADM #2 and the ADM #3.

Fig. 26 shows a state that the channel is recovered using the span switching operation of the BPSR (Bi-directional Path Switched Ring).

The recovery using the span switching operation is performed by transmitting a signal using a protection line in a transmission section where the work line is disconnected. That is, an optical ADM apparatus connected to a transmission line on which a fault takes place transmits a signal to a protection line of transmission lines and receives a signal from a protection line thereof.

According to the embodiment, the ADM #2 and the ADM #3 perform the above-described operation. As a result, a signal that flows from the ADM #2 to

the ADM #3 and a signal that flows from the ADM #3 to the ADM #2 are transmitted using the protection lines.

Fig. 27 is a schematic diagram showing an operation of an optical ADM apparatus that performs the recovering operation shown in Fig. 26. Here, a switching operation that the ADM #2 shown in Fig. 26 performs.

When the network is in the state shown in Fig. 20A, the ADM #2 outputs a signal received through the inter-station line (W-right) to the inter-station line (W-right) and outputs a signal received through the inter-station line (W-left) to the inter-station line (W-left). At this time, as shown in Fig. 20B, if faults take place on the work lines (W-right and W-left) between the ADM #2 and the ADM #3, the ADM #2 cannot receive a signal transmitted from the ADM #3. In other words, the ADM #2 cannot receive a signal through the inter-station line (W-left). In this case, when the ADM #2 detects this situation and determines that the protection lines are normal, the ADM #2 controls each switch as follows.

The 2 x 1 switch 22a is placed in the "bar state". The 2 x 2 switch 23a is placed in the

"cross state". The 2 x 2 switch 24a is placed in the "bar state". The 2 x 1 switch 22c is placed in the "cross state". The 2 x 2 switch 23c is placed in the "bar state". As a result, when the signal
 5 transmitted from the ADM #1 is input to the ADM #2 through the inter-station line (W-right), as denoted by a solid line in Fig. 27, the signal is guided to the inter-station line (P-right) through the 2 x 1 switch 22a, the 2 x 2 switch 23a, the 2 x
 10 2 switch 24a, the 2 x 1 switch 22c, and the 2 x 2 switch 23c.

The above-described switching operation is also performed by the ADM #3. However, the ADM #3 performs the switching operation in such a manner
 15 that a signal transmitted from the ADM #4 through the inter-station line (W-left) is guided to the inter-station line (P-left). Thus, the ADM #2 receives the signal transmitted from the ADM #4 through the inter-station line (P-left). The ADM #2
 20 controls each switch as follows.

The 2 x 1 switch 22d is placed in the "bar state". The 2 x 2 switch 23d is placed in the "cross state". The 2 x 2 switch 24b is placed in the "bar state". The 2 x 1 switch 22b is placed in
 25 the "cross state". The 2 x 2 switch 23b is placed

in the "bar state". Thus, when the signal that is transmitted from the ADM #4 is input to the ADM #2 through the inter-station line (P-left), as denoted by a dotted line in Fig. 27, the signal is guided
5 to the inter-station line (W-left) through the 2 x 1 switch 22d, the 2 x 2 switch 23d, the 2 x 2 switch 24b, the 2 x 1 switch 22b, and the 2 x 2 switch 23b.

Likewise, the switching operation is also
10 performed by the ADM #3. However, the ADM #3 performs the switching operation in such a manner that a signal transmitted through the inter-station line (P-right) is guided to the inter-station line (W-right).

15 In such a manner, the optical ADM apparatus according to the embodiment can recover from a fault by the span switching operation of the BPSR.

According to the present invention, since a switch circuit is composed in a combination of
20 small optical devices, an optical ADM apparatus with high reliability can be accomplished. Even if a part of optical devices that compose a switch circuit must be replaced, since the other optical devices can be still operated, change or stop of
25 communication services can be minimized.

Although the present invention has been shown
and described with respect to a best mode
embodiment thereof, it should be understood by
those skilled in the art that the foregoing and
5 various other changes, omissions, and additions in
the form and detail thereof may be made therein
without departing from the spirit and scope of the
present invention.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2220
2221
2222
2223
2224
2225
22